



**Power  
Generation**



3 PHASE OUTPUTS					
GENERATOR SET MODEL	RATING	50HZ		60HZ	
		KVA	KW	KVA	KW
<b>WPSC-330S</b>	STAND-BY	330	264	NA	NA
	PRIME	300	240	NA	NA

Ratings at 0.8 pf - Generator designed to operate in ambient temperatures up to 50 °C

Standard Voltages 380 – 415 Volts 3 Phase 50/60HZ

RATING DEFINITIONS:

### PRIME POWER

These ratings are applicable for supplying continuous power (at variable load) in Lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

### STANDBY POWER

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these rating. When used at standby Rating the alternator will be peak continuous rated (according to ISO3046)

### TECHNICAL DATA (50HZ)

Engine model:	QSL9G5	Cooling system:	water	
Engine manufacturer:	Cummins	Total coolant capacity:	(liters)	15
Emissions statement	NA	Total lubrication system capacity:	(liters)	26.4
Number of cylinders:	6	Engine rotation (viewed facing flywheel):	Anti-clockwise	
Cylinder arrangement	Vertical in-line	Engine speed:	RPM	1500
Aspiration:	Turbocharged	Output rated(prime) power:	KW	310
Combustion system	direct injection	Fuel consumption at: 50% load	L/h	31
Compression ratio	14.5:1	75% load:	L/h	46
Bore/stroke:	mm. 114/145	100% load:	L/h	63
Displacement:	(liters) 8.9	Specific lube oil consumption:	Max 0.8% of fuel Consumption	

## STANDARD SPECIFICATION WPSC-330S

### 1. ENGINE

Cummins heavy duty diesel engine.

#### 1.1 Governor

Electronic, compliance with ISO8528, Class G2.

### 2. COOLING RADIATOR

Radiator and cooling fan complete with protection guards, designed to cool the engine in ambient temperatures up to 50° C.



The radiator is mounted on the base frame to avoid vibrations coming from the engine.

### 3. FILTRATION SYSTEM

Cartridge type air filter with security element. Cartridge fuel filter and full lube oil filter. All filters have replaceable elements.

### 4. EXHAUST SYSTEM

Heavy-duty industrial silencer.

### 5. ELECTRICAL SYSTEM

24 Volt DC system with battery charging alternator, Starter motor, High capacity maintenance free lead acid battery, battery rack mounted on the generating set base frame, and heavy duty interconnecting cables with terminations.



Dubai World Central

P.O.Box 390667, Jabel Ali, UAE

Tel: +971-4-8823555

Fax: +971-4-8879484

[sales@worldpowersolution.com](mailto:sales@worldpowersolution.com)

[www.worldpowersolution.com](http://www.worldpowersolution.com)

**6. ALTERNATOR** Screen protected and drip-proof, self-exciting, self-regulating brush-less alternator. Four poles, STAR winding connection, suitable for tropical, humid and saline climates. H class insulation IP23.

### 7. AUTOMATIC VOLTAGE REGULATOR

Static electronic design voltage regulator. Steady voltage precision within + 1 % from no load to full load including cold and hot variations, at any Power factor between 0.8 and unity.

### 8. MOTOR STARTING

An overload capacity equivalent to between 160% to 300% of full load impedance at zero power factor can be sustained for 10 seconds.

### 9. MOUNTING ARRANGEMENT

#### 9.1 Base Frame

The complete generating set is mounted on heavy duty steel fabricated base frame Which is anti rust coated.

#### 9.2 Coupling

Engine and alternator are directly coupled by means of SAE flange so there is no possibility of misalignment after prolong use. The engine fly wheel is flexibly coupled to the alternator rotor.

#### 9.3 Anti Vibration Mounting Pads

Anti vibration pads are fitted between engine-alternator base frame ensuring complete vibration isolation of rotating assemblies.

### 10. FUEL SYSTEM

Metal Fuel tank of 510 litres capacity. The Fuel tank is easy to clean and is equipped with visual fuel level indicator.

### 11. DIMENSIONS

#### Open Type

Length	2650 mm
Width	990 mm
Height	1710 mm
Weight	2200 Kg

#### Silent type

Length	3150 mm
Width	1000 mm
Height	1540 mm
Weight	3125 Kg

### 12. CONTROL PANEL

The manual starting control panel (DSE6020) has been designed and built to combine all the instruments control and the warning lights for engine and alternator. The sheet steel made panel is carefully painted for tropical climates and is designed for a dusty environment. Includes following equipment Ammeter with selector switch – water temperature meter – oil pressure meter- moulded case three pole circuit breaker with thermal and magnetic release - automatic shut down in case of HWT, LOP and over speed - starting key and stop push button - acoustical signal - warning light for high cooling water temperature, low oil pressure, battery charging - hours meter



Automatic starting control board versions are available as option.

### 13. DOCUMENTATION

A full set of operation and maintenance manual are provided.

### 14. FACTORY TESTS


Generating set is subject to a strict load test before delivery. A test certificate can be provided as optional.

### 15. QUALITY STANDARDS

Generating set meets the following standards ISO 8528, IEC 34.1, CEI 2.3, VDE 0530, BS 4999-5000, NF51-100. Cummins is fully accredited ISO 9001 company.

### 16. WARRANTY

Generating set is guaranteed for a period of 12 months from date of commissioning



**Power  
Generation**